

### **PRODUCT HIGHLIGHTS**

- · Built-In LAN
- New Opera TV Apps
- Blu-ray™

### **KEY FEATURES**

### **QUICK START MODE**

Your Smart Blu-ray™ player is ready when you are with a start-up time of 0.5 seconds – compared to nearly 10 seconds for most Blu-ray™ players.

#### **SMART BLU-RAY PLAYER**

Turn any TV into the ultimate home entertainment hub with full access to all your favorite web and TV content, including games, movies, smart apps, and videos.\*

## OPERA™ APPS

Choose from a wide selection of 250+ apps from the Opera™ TV Store and turn any TV into a Smart TV. Stream content from all your favorite TV Opera Apps\*

## **USB**

Connect and share all your stored audio files from any USB storage drive or external hard drive directly to your Blu-ray™ player. Turn your home entertainment system into your personal content showcase.

### **HDMI®**

Enjoy your favorite movies, shows, and sports with higher quality audio. The HDMI® connection transmits digital video and audio over a single cable, delivering a superior entertainment experience.

## **DTS**™ **SURROUND**

Decodes DTS-encoded content, such as TV shows, Blu-ray movies, and streaming media, and processes stereo content to deliver an optimized surround sound experience with enhanced bass response, clear dialog, and consistent volume levels.

### DOLBY® TRUE HD

Enjoy near studio-quality HD audio with your home entertainment system.

# MODEL: BD-J5100/ZA **UPC CODE:** 887276074382

# **DIMENSIONS (INCHES WxHxD):**

• **SET SIZE:** 11.46 x 1.57 x 8.7

• **PACKAGE SIZE:** 12.87 x 3.07 x 11.46

### **WEIGHT (LBS):**

• **SET WEIGHT:** 2.43

PACKAGE WEIGHT: 3.53

## **COMPATIBILITY - PLAYBACK FORMATS:**

MPEG-2

MPO

MPEG-4

MP3

JPEG

LPCM

 HD-JPEG • AVCHD 1.0 AAC

MVK

WMAFLAC

WMV

#### **COMPATIBILITY - PLAYBACK MEDIA:**

- BLU-RAY VIDEO
- DVD-VIDEO
- DVD±R
- DVD±RW

# **POWER CONSUMPTION:**

- **STAND BY:** 0.4
- **OPERATING**: 9.8
- RATING VOLTAGE: AC110-120V~50/60HZ

## **ACCESSORIES INCLUDED IN BOX:**

- REMOTE CONTROLLER: TM1241
- **HDMI CABLE:** NO
- **BATTERY:** YES